

Indala Prox 125 kHz Proximity – Credentials

Indala Prox



	FlexCard*	FlexISO	FlexISO XT	FlexISO* MIFARE*	FlexISO* DESFire™	FlexISO* iCLASS*	FlexTag™	FlexKey*
Base Part Number	FPCRD	FPISO	FPIXT	FPMXI	FPDXI	202X-IND	FPTAG	FPKEY
Read Range: *								
Wallswitch Reader	Up to 5" (12 cm)	Up to 5" (12 cm)	Up to 4" (10 cm)			Up to 3" (7 cm)		Up to 2" (5 cm)
Classic Reader	Up to 5" (12 cm)					Up to 3" (7 cm)	Up to 2" (5 cm)	
Mullion (Slim) Reader	Up to 5" (12 cm)					Up to 3" (7 cm)	Up to 2" (5 cm)	
Mid-Range Reader	Up to 12" (30 cm)					Up to 7" (17 cm)		
Long-Range Reader	Up to 25" (63 cm)	Up to 26" (66 cm)		Up to 24" (61 cm)			Up to 14" (35 cm)	Up to 16" (40.64 cm)
Heavy-Duty PinProx Keypad Reader	Up to 3.75" (9.52 cm)					Up to 1.75" (4.45 cm)	Up to 3.5" (8.89 cm)	
Membrane Keypad Reader	Up to 4" (10 cm)					Up to 3" (7 cm)	Up to 3.5" (8.89 cm)	
Memory Size/ Application Areas	N/A			1k Byte (8,192 bits) or 4k Bytes (32,768 bits) MIFARE 1k: memory arranged in 16 64-byte Sectors MIFARE 4k: memory arranged in 40 Sectors: 32 sectors of 64 bytes, 8 sectors of 256 bytes	4k Bytes (32,768 bits)	2k bit (256 Byte) card – 2 application areas 16k bit (2k Byte) – 2 or 16 application areas 32k bit (4k Byte) card – 16k bit in 2 or 16 application areas plus 16k bit user configurable.	N/A	
HID Proximity 125 kHz	Yes							
Contact Smart Chip Module Embeddable	Optional						No	
Wiegand Strip	No							Yes
Magnetic Stripe	No	Optional					No	
Printable **	Yes						No	
Slot Punch	Vertical	Horizontal or Vertical optional		Vertical optional			No	Keyring
Visual Security Options	Yes						N/A	
Warranty	Lifetime	Two Years	Lifetime	Two Years			Lifetime	

* Dependant upon installation conditions. **Some types of printing processes can take these credentials out of ISO compliance for thickness. Consult factory for more information.